

AD-A163 107


SIMPLE EFFECTIVE COMPUTATION OF PRINCIPAL EIGENVECTORS
AND THEIR EIGENVAL (U) RHODE ISLAND UNIV KINGSTON DEPT
OF ELECTRICAL ENGINEERING D W TUFTS ET AL OCT 85
N00014-83-K-0664


1/1

UNCLASSIFIED

F/G 12/1

NL





MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

FINAL REPORT

2

SIMPLE, EFFECTIVE COMPUTATION OF PRINCIPAL EIGEN-VECTORS AND THEIR
EIGENVALUES AND APPLICATION TO HIGH-RESOLUTION ESTIMATION OF FREQUENCIES

AD-A163 107

Donald W. Tufts
Costas D. Melissinos

Department of Electrical Engineering
University of Rhode Island
Kingston, Rhode Island 02881

October 1985

Probability and Statistics Program
Electronics Program
Office of Naval Research
Arlington, Virginia 22217
under Contracts N00014-83-K-0664 & N00014-84-K-0445
D.W. Tufts, Principal Investigator

&

partially supported
under Contract ECS-8408997, NSF

DTIC FILE COPY

DTIC
ELECTE
JAN 14 1986

A

Approved for public release; distribution unlimited

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER	2. GOVT ACCESSION NO. ADA 163 107	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Simple, Effective Computation of Principal Eigenvectors and their Eigenvalues and Application to High-Resolution Estimation of Frequencies		5. TYPE OF REPORT & PERIOD COVERED October 1984 - October 1985
7. AUTHOR(s) D.W. Tufts C.D. Melissinos		6. PERFORMING ORG. REPORT NUMBER
9. PERFORMING ORGANIZATION NAME AND ADDRESS Department of Electrical Engineering University of Rhode Island Kingston, RI 02881		8. CONTRACT OR GRANT NUMBER(s) N00014-83-K-0664 N00014-84-K-0445 ECS-8408997
11. CONTROLLING OFFICE NAME AND ADDRESS Probability and Statistics Program; Electronics Program Office of Naval Research (Code 411SP) Dept. of the Navy, Arlington, VA 22217		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
14. MONITORING AGENCY NAME & ADDRESS (If different from Controlling Office)		12. REPORT DATE October 1985
		13. NUMBER OF PAGES 30
		15. SECURITY CLASS. (of this report) Unclassified
		15a. DECLASSIFICATION/DOWNGRADING SCHEDULE
16. DISTRIBUTION STATEMENT (of this Report)		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report) Approved for public release; distribution unlimited.		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Prony's method, Lanczos method, High-Resolution Estimation, Linear Prediction, Power method, Singular Value-Decomposition, Computational Complexity, Operation Count.		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) We present the results of an investigation of the Prony-Lanczos (P-L) method 14,38 and the power method 39 for simple computation of approximations to a few eigenvectors and eigenvalues of a Hermitian matrix. We are motivated by realization of high-resolution signal processing in an integrated circuit. The computational speeds of the above methods are analyzed. They are completely dependent on the speed of a matrix-vector product operation. If only a few eigenvalues or eigenvectors are needed, the suggested methods can substitute for the slower methods of the LINPACK or EISPACK subroutine		

libraries. The accuracies of the suggested methods are evaluated using matrices formed from simulated data consisting of two sinusoids plus gaussian noise. Comparisons are made with the corresponding eigenvalues and eigenvectors obtained using LINPACK. Also the accuracies of frequency estimates obtained from the eigenvectors are compared.

RECEIVED	
DATE	
TIME	
BY	
FOR	
ALL	

QUALITY ASSURED

Simple, Effective Computation of Principal Eigenvectors and their Eigenvalues
and Application to High-Resolution Estimation of Frequencies

D.W. Tufts and C.D. Melissinos

Department of Electrical Engineering
University of Rhode Island
Kingston, RI 02881

Abstract

We present the results of an investigation of the Prony-Lanczos (P-L) method [14,38] and the power method [39] for simple computation of approximations to a few eigenvectors and eigenvalues of a Hermitian matrix. We are motivated by realization of high-resolution signal processing in an integrated circuit. The computational speeds of the above methods are analyzed. They are completely dependent on the speed of a matrix-vector product operation. If only a few eigenvalues or eigenvectors are needed, the suggested methods can substitute for the slower methods of the LINPACK or EISPACK subroutine libraries. The accuracies of the suggested methods are evaluated using matrices formed from simulated data consisting of two sinusoids plus gaussian noise. Comparisons are made with the corresponding eigenvalues and eigenvectors obtained using LINPACK. Also the accuracies of frequency estimates obtained from the eigenvectors are compared.

This work was supported in part by the Electronics Program of the Office of Naval Research.

I. Introduction

We are motivated by the use of eigenvector decompositions of data matrices or estimated covariance matrices for detection of signals in noise and for estimation of signal parameters. This has evolved from early work of Liggett [1] and Owsley [2], to adaptive-array-detection improvements of Tufts and Kirsteins [3,33] and high-resolution parameter estimators of Cantoni and Godara [4], Bienvenu and Kopp [5], Owsley [6], Schmidt [21] and Tufts and Kumaresan [7,32].

Principal component analysis, using principal eigenvalues and eigenvectors of a matrix, was initiated by Karl Pearson (1901) [8], and Frisch (1929) [9] in the problem of fitting a line, a plane or in general a subspace to a scatter of points in a higher dimensional space. Eckart and Young [34] presented the use of singular value decomposition for finding low-rank approximations to rectangular matrices. C.R. Rao examined the applications of principal component analysis [10]. Eigenvector analysis is also used in image processing to provide efficient representations of pictures [11]. Recently, principal component analysis has been coupled with the Wigner mixed time-frequency signal representation to perform a variety of signal processing operations [28,30,31].

Linear Prediction techniques for estimation of signal parameters, which are modern variants of Prony's method, can be improved using eigenvector decomposition [7]. Prony's method is a simple procedure for determining the values of parameters of a linear combination of exponential functions. Now "Prony's method" is usually taken to mean the least squares extension of the method as presented by Hildebrand [13]. The errors in signal parameters which are estimated by Prony's method can be very large [14]. If the data is composed of undamped sinusoids, the forward and backward prediction

equations and a prediction order larger than the number of signal components can be used simultaneously as advocated by Nutall [22], Ulrych and Clayton [23], and Lang and McClellan [24]. Tufts and Kumaresan have shown how one can improve such methods of parameter estimation by going through a preprocessing step before application of Prony's method [7,15,16,17]. The measured data matrix or the matrix of estimated covariances is replaced by a matrix of rank M , which is the best least squares approximation to the given matrix. If there is no prior information about the value of M , it is estimated from the data using singular value decomposition (SVD).

The eigenvalue problem [37] is one area where extensive research has been done and well established algorithms are available in highly optimized mathematical libraries such as LINPACK and EISPACK [40]. The computational complexity of these algorithms is of order $O(N^3)$ where N is the size of the matrix. They solve for the complete set of eigenvalues and eigenvectors of the matrix even if the problem requires only a small subset of them to be computed. For the above applications, only a few principal eigenvectors and eigenvalues are needed. Hence, we would like to use a method which uses this specialization to reduce the computations.

Tufts and Kumaresan [29,32,33] have suggested procedures for improving Prony's method without computation of eigenvectors. These appear to perform about the same as the more complicated approaches which use eigenvalue and eigenvector decomposition. The approach in [29] is based on the results of Hocking and Leslie for efficient selection of a best subset [25]. The approach of [32] and [33] is based on the simple computations which result from using the longest possible prediction interval.

Here we investigate two different approaches to achieving SVD-like improvement to Prony's method without the computational cost of actually computing the SVD or computing all eigenvectors and eigenvalues. The idea is to calculate the few, necessary eigenvalues and eigenvectors using the power method [39] and a method of Lanczos [14]. Our derivation of Lanczos' method stresses the connection with Prony's method. The methods are analyzed and their amounts of computation are calculated. Simulations are performed and results are compared to the singular value decomposition method in LINPACK.

II. The Prony-Lanczos Method

Let us assume that we start with a given square, Hermitian matrix A for which we want to compute the principal eigenvectors and eigenvalues. For examples, this could be either the true underlying, population covariance matrix or the estimated covariance matrix [36] from spatial or temporal data. Let us also define the eigenvectors and eigenvalues associated with the matrix A (dimension $A=n$).

$$A\mathbf{u}_i = \lambda_i \mathbf{u}_i, \quad i = 1, 2, \dots, n \quad (1)$$

where $\mathbf{u}_i^* \cdot \mathbf{u}_j = 0, \quad i \neq j$

$$\mathbf{u}_i^* \cdot \mathbf{u}_j = 1, \quad i = j, \quad \text{that is } \mathbf{u}_i \text{ are orthonormal vectors.} \quad (2)$$

The asterisk is used to denote a complex conjugate transpose.

The characteristic polynomial associated with the matrix A is given by

$$\det(A - \lambda I) = 0 \quad (3)$$

Expanding the determinant we have the polynomial equation

$$\lambda^n + p_{n-1} \lambda^{n-1} + \dots + p_0 = 0 \quad (4)$$

and the roots of this polynomial will give us the eigenvalues λ_i of the matrix. We briefly summarize the procedure for obtaining the eigenvalues λ_i

based on the Lanczos "power sums" as presented in [14]. We shall show that the eigenvalues can then be obtained from the power sums by Prony's method [13].

Let us select a starting vector \underline{b}_0 . We assume that the starting vector \underline{b}_0 has a non-zero projection on the eigenvectors of the matrix A corresponding to the eigenvalues that we want to compute.

We then analyze the vector \underline{b}_0 in the reference system of the vectors $\{\underline{u}_i\}$, which are the set of orthonormal eigenvectors of the matrix A:

$$\underline{b}_0 = \tau_1 \underline{u}_1 + \tau_2 \underline{u}_2 + \dots + \tau_n \underline{u}_n \quad (5)$$

where

$$\tau_i = \underline{u}_i^* \underline{b}_0 \quad (6)$$

Hence, using equation (1), successive vectors formed by premultiplications of \underline{b}_0 by powers of the matrix A can be represented as follows :

$$\begin{aligned} \underline{b}_1 &= A \underline{b}_0 = \tau_1 \lambda_1 \underline{u}_1 + \tau_2 \lambda_2 \underline{u}_2 + \dots + \tau_n \lambda_n \underline{u}_n \\ \underline{b}_2 &= A^2 \underline{b}_0 = A \underline{b}_1 = \tau_1 \lambda_1^2 \underline{u}_1 + \tau_2 \lambda_2^2 \underline{u}_2 + \dots + \tau_n \lambda_n^2 \underline{u}_n \\ &\vdots \\ \underline{b}_{k+1} &= A^k \underline{b}_0 = A \underline{b}_k = \tau_1 \lambda_1^k \underline{u}_1 + \tau_2 \lambda_2^k \underline{u}_2 + \dots + \tau_n \lambda_n^k \underline{u}_n \end{aligned} \quad (7)$$

Let us form the set of basic scalars:

$$c_{i+k} = \underline{b}_i^* \underline{b}_k = \underline{b}_k^* \underline{b}_i \quad (8)$$

Then we shall have:

$$c_k = |\tau_1|^2 \lambda_1^k + |\tau_2|^2 \lambda_2^k + \dots + |\tau_n|^2 \lambda_n^k = \underline{b}_0^* A^k \underline{b}_0 \quad (9)$$

which were called by Lanczos the "weighted power sums" [14].

The problem of obtaining λ_i 's from the c_i 's is the "problem of weighted moments" [14]. That is the problem of Prony [12] and the old and modern versions of Prony's method can be used to estimate the λ_i 's.

The prediction-error-filter equations of Prony's method can be written as follows:

$$\begin{aligned}
c_0 g_0 + c_1 g_1 + \dots + c_{n-1} g_{n-1} + c_n &= 0 \\
c_1 g_0 + c_2 g_1 + \dots + c_n g_{n-1} + c_{n+1} &= 0 \\
\vdots & \\
c_n g_0 + c_{n+1} g_1 + \dots + c_{2n-1} g_{n-1} + c_{2n} &= 0
\end{aligned} \tag{10a}$$

or in matrix form,

$$C \cdot g = 0 \tag{10b}$$

A non-zero solution is possible if the determinant of C is zero.

From the theory of Prony's method [13]

$$g(\lambda_i) = \lambda_i^n + g_{n-1} \lambda_i^{n-1} + \dots + g_1 \lambda_i + g_0 = 0 \tag{11}$$

hence the polynomial coefficient vector \underline{g} is also orthogonal to the vector $\{1 \lambda_i \lambda_i^2 \dots \lambda_i^n\}^T$ where λ_i 's are the eigenvalues of the matrix A.

Lanczos noticed that Prony's method can be simplified if we substitute the sequence $\{1 \lambda_i \lambda_i^2 \dots \lambda_i^n\}$ for a row of the matrix C to form a matrix C'. If we replace the matrix C by C' in (10b), the non-zero vector \underline{g} is still a solution, because of (11). Hence the determinant of C' must be zero.

$$\det C' = \begin{vmatrix} 1 & \lambda_i & \lambda_i^2 & \dots & \lambda_i^n \\ c_0 & c_1 & c_2 & \dots & c_n \\ \vdots & \vdots & \vdots & \vdots & \vdots \\ c_{n-1} & c_n & \dots & \dots & c_{2n-1} \end{vmatrix} = p'(\lambda_i) = 0 \tag{12}$$

Hence, the λ_i 's can be obtained directly by finding the zeros of the polynomial $p'(z)$. That is, Lanczos showed that it is not necessary to first

solve equations (10) for the prediction-error-filter coefficients.

Thus, in the absence of noise, we know that entering the weighted power sums c_k of (8) in equation (12) and finding the roots of the resulting polynomial will provide us with accurate estimates of the true eigenvalues λ_i of the covariance matrix A . Note also, that equation (12) can be reduced to a 2nd order equation involving only c_0, c_1, c_2, c_3 and still provide us with accurate solutions for our problem of estimating one or two sinusoids.

Now, if our data is composed of one or two complex sinusoids, then the $(L \times L)$ covariance matrix elements will be also one sinusoid or a sum of two sinusoids, hence the rank of the matrix will be one or two, respectively. The eigen-decomposition of the matrix will show that it has only one or two non-zero eigenvalues and hence it can be characterized by a linear combination of one or two eigenvectors, corresponding to the principal non-zero eigenvalues. In Appendix A it is shown that these eigenvectors can be expressed as a linear combination of complex sinusoids which have frequencies equal to these of the sinusoids composing the data.

Now, suppose that we have accurately determined a few eigenvalues, say two, λ_1 and λ_2 , from the $(n \times n)$ matrix A . We wish to determine the corresponding eigenvectors. Two concepts are used : (a) premultiplication of a vector by the matrix $(A - \lambda_i I)$ removes the i^{th} eigenvector component of that vector and (b) if a vector, to a good approximation, consists only of M eigenvector components, then removing $(M-1)$ of these components leaves one, isolated eigenvector component.

Let us consider the special case of a rank two matrix :

$$A = \lambda_1 \underline{u}_1 \underline{u}_1^* + \lambda_2 \underline{u}_2 \underline{u}_2^* \quad (13)$$

From equations (5) and (13) we have:

$$A\mathbf{b}_0 = \tau_1\lambda_1\mathbf{u}_1 + \tau_2\lambda_2\mathbf{u}_2 \quad (14)$$

Then, our preliminary, unnormalized estimates of the two principal eigenvectors are :

$$\begin{aligned} \mathbf{u}_1' &= (A - \lambda_2 I) A\mathbf{b}_0 = (A - \lambda_2 I)(\tau_1\lambda_1\mathbf{u}_1 + \tau_2\lambda_2\mathbf{u}_2) = \\ &= \tau_1\lambda_1^2\mathbf{u}_1 + \tau_2\lambda_2^2\mathbf{u}_2 - \tau_1\lambda_1\lambda_2\mathbf{u}_1 - \tau_2\lambda_2^2\mathbf{u}_2 = \\ &= \tau_1\lambda_1(\lambda_1 - \lambda_2)\mathbf{u}_1 \end{aligned} \quad (15)$$

And similarly for the second eigenvector estimate we have :

$$\mathbf{u}_2' = \tau_2\lambda_2(\lambda_2 - \lambda_1)\mathbf{u}_2 \quad (16)$$

Normalizing the eigenvectors \mathbf{u}_i' ($i=1,2$) we can write (15) and (16) as

$$\mathbf{u}_1' = e^{j\theta_1} \mathbf{u}_1 \quad ; \quad \theta_1 = \text{angle of } \tau_1\lambda_1(\lambda_1 - \lambda_2) \quad (17)$$

$$\mathbf{u}_2' = e^{j\theta_2} \mathbf{u}_2 \quad ; \quad \theta_2 = \text{angle of } \tau_2\lambda_2(\lambda_2 - \lambda_1) \quad (18)$$

In general ,given the required eigenvalues from the earlier Prony calculation, we estimate an unnormalized k^{th} eigenvector from the formula :

$$\mathbf{u}_k' = \prod_{i \neq k} (A - \lambda_i I) A\mathbf{b}_0 \quad (19)$$

where the number of factors in the product depends on the number of significant eigenvector components in Ab_0 .

Finally, a few comments should be made on the selection of the starting vector b_0 . Our sole assumption until now has been that b_0 has a non-zero projection on some eigenvector of A that we want to compute. A good b_0 vector would have to be biased in favor of the principal eigenvectors. We have found that the Fourier vector provides a very good selection for b_0 . This vector will have its fundamental frequency computed from the maximum peak of the DFT data spectrum. Very frequently in signal processing applications the data is preprocessed through a DFT step for a coarse analysis. This is a valuable bonus for our method to use the available information for further processing.

III. The Power Method

Suppose A is a Hermitian ($n \times n$) matrix. The SVD theorem [37] states that A can be written as:

$$A = U \cdot S \cdot U^T \quad (20)$$

where U is a unitary matrix and S is a matrix consisting of real only diagonal elements [37].

The power method computes the dominating singular vectors one at a time and is based on solving the equation:

$$su = Au \quad (21)$$

for the singular vector \underline{u} and the singular value s . The power method uses an iterative scheme to solve (21). We instead suggest a two-step solution using an appropriate starting vector \underline{b}_0 :

$$\underline{u}_1 = A \underline{b}_0 / \|A \underline{b}_0\| \quad (22)$$

The singular value is chosen to be:

$$s_1 = \|A \underline{b}_0\| \quad (23)$$

In order to obtain the next singular vector, the estimated singular plane $(\underline{u}_1 \underline{u}_1^T)$ is removed from A using the following deflation procedure [37]:

$$A' = A - s_1 \underline{u}_1 \underline{u}_1^T \quad (24)$$

and the procedure is repeated with matrix A to yield s_2, \underline{u}_2 .

The selection of \underline{b}_0 is very important and the Fourier vector provides a very good estimate. This preprocessing step can be implemented in VLSI very efficiently using summation-by-parts [28] or the Fast Hartley Transform [42,43] methods. A necessary thing required to implement the power method is a circuit capable of computing matrix vector products of the form $A\underline{u}$. But the rounding errors associated with it are always worrisome limiting the usefulness of the power method. For this reason we propose to use the permuted difference coefficients (PDC) algorithm [26,27] coupled with the known Fourier vector to perform the above operation with high accuracy and no round-off errors. A VLSI implementation for the PDC algorithm can be easily realized using a random access memory (RAM) together with a read-

only-memory (ROM) where the original Fourier coefficients and the subsequent reordered coefficients addresses are stored.

IV. Operation count

In this section we calculate the total operations needed for the singular value decomposition (LINPACK), the Prony-Lanczos method and the Power method.

(1). The matrix eigenvalue problem has been solved in both LINPACK and EISPACK mathematical libraries. The LINPACK SVD routine is presented here. The solution can be divided in three steps: reduction to bidiagonal form, initialization of the right and left unitary matrices U and V and the iterative reduction to diagonal form.

The reduction to bidiagonal form has the following floating point multiplication count (for a square NxN matrix):

$$2[N^3 - N^3/3]$$

Approximately the same number of additions are required.

In the second step the amount of work involved when only the right-hand side matrix V is computed, is:

$$2N^3/3$$

floating point multiplies and approximately the same number of additions.

In the last step rotations are used to reduce the bidiagonal matrix to diagonal form. Thus the amount of work depends on the total number of

rotations needed. If this number is r , then we have the following multiplication counts:

$$4Nr$$

The number r is quite difficult to estimate. There exists an upper bound for r ,

$$r \leq sN^2/2$$

where s is the maximum number of iterations required to reduce a superdiagonal element as to be considered zero by the convergence criterion.

Hence the total operation count for the LINPACK SVD solution is:

$$2N^3 + 4Nr \leq 2N^3(s+1) \text{ flops}$$

where by the term "flop" we denote a floating point multiply-add operation.

(2). The Prony-Lanczos method is entirely dependent on the speed of a matrix-vector product operation. For a rank two square matrix of size N we shall have:

The matrix-vector multiplications to determine the vectors \underline{b}_i involve N floating point multiplications and $(N-1)$ floating point additions per row for a total of :

$$N^2 \text{ flops}$$

($2N^2$ flops for the two vectors $\underline{b}_1, \underline{b}_2$). The scalar weights $c_i, i=0,1,2,3$

require vector-vector inner products for a count of N multiplications and $(N-1)$ additions per weight . Therefore the total is:

$$4N \text{ flops}$$

The computation of the eigenvalues from the (second order) determinant condition involves 12 flops and one square root calculation. Finally, the eigenvector computation requires N flops for each vector for a total of $2N$ flops.

Hence the total operation count for the Prony-Lanczos procedure requires:

$$(2N^2+6N+12) \text{ flops} + 1 \text{ square root}$$

The above computations do not include the work required to select the starting vector \underline{b}_0 using a DFT analysis. In this case, assuming a data sequence zero padded to M points, we shall have:

$$M \log_2 M \text{ flops}$$

plus $(M-1)$ additions for the determination of the maximum spectral peak.

(3). The power method computes the dominating eigenvalues and eigenvectors one pair at a time . The second pair will be computed following a deflation of A . In general, the number of iteration steps depend on the convergence criterion severity . We instead claim that two-steps are generally enough to provide sufficient accuracy. The Fourier vector is again selected as the starting vector \underline{b}_0 .

The first eigenvalue/eigenvector pair requires $2N^2+2N$ flops. The deflation step requires N^2 flops and N^2 floating point additions.

Hence (for a rank two matrix) the power method requires a total of

$$5N^2+4N \text{ flops}$$

plus N^2 floating point additions.

V. Simulation results

Let us assume that we have a data sequence which is composed of uniformly spaced samples of two closely spaced complex sinusoids in white noise. We shall follow the methods described earlier in section II & III to calculate the principal eigenvalues and eigenvectors.

The data sequence is given by the equation

$$x(n) = \exp(j2\pi f_1 n + \phi_1) + \exp(j2\pi f_2 n + \phi_2) + w(n) \quad (25)$$

with $f_1 = 0.52\text{Hz}$, $f_2 = 0.5\text{Hz}$ and for $n=1,2,\dots,25$

Here, 25 data samples are used and the phase difference is $\Delta\phi = \pi/2$ computed at the middle of the data set, effectively reducing the signal-to-noise ratio in that region, thereby representing the worst case that can be encountered. The frequency separation is less than the reciprocal of the observation time. The data is zero padded to $m=128$ points and then the maximum peak of the DFT is computed to yield the frequency of the Fourier vector. This vector will be used as a starting eigenvector for the P-L and Power methods later.

We construct the forward plus backward augmented covariance matrix A of

size (21x21) . Its effective rank is two. The SVD routine ,the P-L method and the Power method are employed to solve for the eigenvalues and eigenvectors (eigenpairs) of the matrix. The P-L method and the Power method compute only the two principal eigenpairs. The mean values and standard deviations of the eigenvalue estimates are given in Table I for an ensemble of 500 experiments. The performance of the P-L and Power methods is almost identical to the SVD (LINPACK) method for the first eigenvalue estimates. At high SNR the second eigenvalue mean and standard deviation estimate obtained from the P-L method is biased with respect to the noiseless SVD results. However ,at low SNR the eigenvalue statistics are closer to the noiseless SVD results than the other two methods.

Table II presents the statistics of the distances of the P-L and Power methods eigenvectors from those of the SVD method. The distance is the inverse cosine of the angle between the subspaces spanned by the estimated eigenvectors [41]. The results show that for the first eigenvector the P-L estimate of the mean is less biased (about one order of magnitude) than the Power method, whereas for the second eigenvector estimates they perform the same. This shows that these vectors span virtually the same subspace as the vectors computed from the SVD method. The eigenvector estimates were also compared to the signal eigenvectors and the distances were computed as above. The results show that at high SNR the eigenvector spanned subspaces have a greater distance from the signal subspace than the SVD subspace. At low SNR the distance is reduced and the second eigenvector statistics are closer to the signal eigenvector than the SVD eigenvector.

Table III shows the CPU time required to compute the eigenvalues/eigenvectors pairs for these methods. The P-L method is faster than the SVD by the order of the size of the covariance matrix, which here

is 21. This roughly agrees with the theoretical operation count we presented in section IV. It is almost twice as fast as the Power method. Inclusion of the FFT computation in these two methods will offset some of their speed advantage over the SVD . Nevertheless ,the P-L method is again about one order of magnitude faster than the SVD method and the Power method a little more than half that (6 times faster).

The frequencies f_i are then obtained from the eigenvectors of the estimated covariance matrix by the T-K method [7]. For both estimates of the mean and standard deviation ,as presented in Table IV,all three methods perform similarly down to 15 db. At 0db the P-L method yields slightly better statistics than the other two methods.

VI. Conclusion

Two methods,the Prony-Lanczos method and the Power method are proposed for simple computation of approximations to a few eigenvectors and eigenvalues of a Hermitian matrix. The computational speeds of these methods were analyzed. The accuracies of the proposed methods were evaluated using covariance matrices from data consisting of two sinusoids in a gaussian noise environment. Comparisons were made with the corresponding eigenvectors and eigenvalues obtained using the LINPACK mathematical library. The suggested methods can substitute for the slower method of LINPACK if a few eigenvalues or eigenvectors are needed.

Appendix A:

In this appendix we derive the eigenvalues and eigenvectors of the covariance matrix R for the case of one and two sinusoids.

One Complex Sinusoid Case:

The data sequence is modelled by:

$$y(n) = a_1 e^{j\omega_1 n}, \quad n = 1, 2, \dots, N$$

The covariance values of $y(n)$ are:

$$r_{yy}(i, j) = \frac{1}{N-L} \sum_{n=L+1}^N y^*(n-i) y(n-j) \quad i, j=1, 2, \dots, L \quad (A.1)$$

Writing the covariance matrix R explicitly in terms of the signal, we have:

$$\begin{bmatrix} |a_1|^2 & |a_1|^2 e^{-j\omega_1} & |a_1|^2 e^{-j\omega_1(L-1)} \\ |a_1|^2 e^{j\omega_1} & |a_1|^2 & |a_1|^2 e^{-j\omega_1(L-2)} \\ \cdot & \cdot & \cdot \\ |a_1|^2 e^{j\omega_1(L-1)} & & |a_1|^2 \end{bmatrix} \quad (A.2)$$

We can diagonalize R by an orthogonal matrix U resulting in the following

equation:

$$U^* R U = \begin{bmatrix} \lambda_1 & & & \\ & \lambda_2 & & \\ & & \ddots & \\ 0 & & & 0 \\ & & & & \ddots & \\ & & & & & \lambda_n \end{bmatrix} \quad (A.3)$$

The eigenvalues of R which occur along the diagonal elements of the above equation, satisfy the following equation:

$$\sum_{i=1}^L \lambda_i = \text{tr}(R) = L |a_1|^2 \quad (A.4)$$

But the covariance matrix R is of rank=1, since it has only one linearly independent row (or column). The rest are obtained by multiplying by a

constant number ($e^{\pm j\omega_1 k}$).

Then the eigenvector corresponding to the eigenvalue $\lambda_1 = L |a_1|^2$ is:

$$\underline{u}_1 = c_1 (1 \quad e^{j\omega_1} \quad e^{2j\omega_1} \quad \dots \quad e^{j(L-1)\omega_1})^T$$

since it annihilates every row of the matrix $(R - \lambda_1 I)$. The constant c_1 can be determined from the fact that the matrix U is orthonormal, hence:

$$\underline{u}_1^* \cdot \underline{u}_1 = 1$$

which yields:

$$c_1 = \frac{1}{\sqrt{L}}$$

Hence finally:

$$\underline{u}_1 = \frac{1}{\sqrt{L}} (1 \quad e^{j\omega_1} \quad e^{2j\omega_1} \quad \dots \quad e^{j(L-1)\omega_1}) \quad (\text{A.5})$$

and this is a Fourier vector with fundamental frequency ω_1 .

Two Complex Sinusoids Case:

The data sequences is modelled by:

$$y(n) = a_1 e^{j\omega_1 n} + a_2 e^{j\omega_2 n} \quad n = 1, 2, \dots, N \quad (A.6)$$

The covariance estimates are given by the expression:

$$r_{yy}(k, m) = \frac{1}{N-L} \sum_{n=L+1}^N y^*(n-k) y(n-m) = |a_1|^2 e^{-j\omega_1(m-k)} + \quad (A.7)$$

$$+ |a_2|^2 e^{-j\omega_2(m-k)} + a_1 a_2^* v_1 + a_2 a_1^* v_2, \quad k, m = 1, 2, \dots, L$$

where:

$$v_1 = \frac{1}{N-L} \sum_{n=L+1}^N e^{j\omega_1(n-m) - j\omega_2(n-k)}$$

$$v_2 = \frac{1}{N-L} \sum_{n=L+1}^N e^{j\omega_2(n-m) - j\omega_1(n-k)}$$

Rewriting the matrix R, we have:

$$R = M_1 M_2 \quad (A.8)$$

(Lx2) (2xL)

where:

$$\begin{aligned}
M_1 &= [|a_1|^2 \underline{e}_1 + x \underline{e}_2 \quad |a_2|^2 \underline{e}_2 + x^* \underline{e}_1] \\
M_2 &= [\underline{e}_1^* \quad \underline{e}_2^*]^T \\
\underline{e}_1 &= [1 \quad e^{j\omega_1} \quad e^{2j\omega_1} \quad e^{j(L-1)\omega_1}]^T \\
\underline{e}_2 &= [1 \quad e^{j\omega_2} \quad e^{2j\omega_2} \quad e^{j(L-1)\omega_2}]^T
\end{aligned}$$

and

$$x = \frac{a_1 a_2^*}{N-L} e^{j(\omega_2 - \omega_1)} \sum_{n=L+1}^N e^{-j(\omega_2 - \omega_1)n}$$

If \underline{u}_1 is an eigenvector of R corresponding to eigenvalue λ_1 , then:

$$M_1 M_2 \underline{u}_1 = \lambda_1 \underline{u}_1 \quad (\text{A.9})$$

Premultiplying by M_2 , we have:

$$M_2 M_1 M_2 \underline{u}_1 = \lambda_1 M_2 \underline{u}_1 \quad (\text{A.10})$$

Thus λ_1 is also the eigenvalue of $M_2 M_1$ and the corresponding eigenvector is:

$$\underline{v}_1 = M_2 \underline{u}_1 \quad (\text{A.11})$$

Premultiplying (A.10) again by M_1

$$M_1 M_2 M_1 \underline{v}_1 = \lambda_1 M_1 \underline{v}_1 \quad (\text{A.12})$$

and comparing (A.10) with (A.12)

$$\underline{u}_1 = M_1 \underline{v}_1 \quad (\text{A.13})$$

Thus we can find the eigenvalues and eigenvectors of R by working with the matrix $M_2 M_1$ which is of order 2. Hence:

$$M_2 M_1 = \begin{bmatrix} L|a_1|^2 + xg & |a_2|^2 g + Lx^* \\ |a_1|^2 g^* + Lx & L|a_2|^2 + x^* g^* \end{bmatrix} \quad (A.14)$$

where

$$g = \sum_{n=0}^{L-1} e^{j(\omega_2 - \omega_1)n} = \sum_{n=0}^{L-1} e^{j \Delta \omega n} \quad (A.15)$$

The eigenvalues λ_1 and λ_2 are found to be:

$$\begin{aligned} \lambda_1 &= 1/2 \{ L|a_1|^2 + L|a_2|^2 + 2\text{Re}\{xg\} + ((L|a_1|^2 + L|a_2|^2 + 2\text{Re}\{xg\})^2 - 4(L^2 - |g|^2)(|a_1|^2|a_2|^2 - |x|^2))^{1/2} \} \\ \lambda_2 &= 1/2 \{ L|a_1|^2 + L|a_2|^2 + 2\text{Re}\{xg\} - ((L|a_1|^2 + L|a_2|^2 + 2\text{Re}\{xg\})^2 - 4(L^2 - |g|^2)(|a_1|^2|a_2|^2 - |x|^2))^{1/2} \} \end{aligned} \quad (A.16)$$

where

$$\text{Re}\{xg\} = \text{Re} \frac{\{a_1 a_2^*\} \cos\left(\frac{N}{2} - 2\right)\Delta\omega \cdot \sin \frac{N-L}{2} \Delta\omega \sin \frac{L\Delta\omega}{2}}{\sin^2 \frac{\Delta\omega}{2}} \quad (A.17)$$

Note that a column of the adjoint of $(M_2 M_1 - \lambda_1 I)$ gives the eigenvector \underline{v}_1 of $M_2 M_1$.

$$\text{Adj}(M_2 M_1 - \lambda_1 I) = \begin{bmatrix} (L|a_1|^2 - xg) - \lambda_1 & -|a_2|^2 g - Lx^* \\ -|a_1|^2 g - Lx & (L|a_2|^2 + x^* g^*) - \lambda_1 \end{bmatrix} \quad (\text{A.18})$$

Therefore the eigenvector \underline{v}_1 is : $\underline{v}_1 = [v_{11} \quad v_{21}]^T$

$$\text{or } \underline{v}_1 = [(L|a_1|^2 + xg) - \lambda_1 \quad -|a_1|^2 g - Lx]^T \quad (\text{A.19})$$

Now the eigenvector \underline{u}_1 of R corresponding to λ_1 is:

$$\underline{u}_1 = M_1 \underline{v}_1$$

and hence,

$$\underline{u}_1 = v_{11} (|a_1|^2 \underline{e}_1 + x \underline{e}_2) + v_{21} (|a_2|^2 \underline{e}_2 + x^* \underline{e}_1). \quad (\text{A.20})$$

a linear combination of the Fourier vectors \underline{e}_1 and \underline{e}_2 .

Similarly, the eigenvector \underline{u}_2 of R corresponding to λ_2 is:

$$\underline{u}_2 = v_{11}' (|a_1|^2 \underline{e}_1 + x \underline{e}_2) + v_{21}' (|a_2|^2 \underline{e}_2 + x^* \underline{e}_1) \quad (\text{A.21})$$

where $\underline{v}_1' = [v_{11}' \quad v_{21}']^T$

and

$$v_{11}' = (L|a_2|^2 + x^* g^*) - \lambda_2 \quad (\text{A.22})$$

$$v_{21}' = -|a_2|^2 g - Lx^*$$

The rest of the eigenvalues of R are zero and the corresponding eigenvectors are not unique.

SNR	SVD	P-L	PM
∞	mean= 22.0357	22.0126	22.0174
	st.dev= 0	0	0
30	22.0636	22.0423	22.0353
	0.2652	0.2655	0.2642
15	22.0341	22.3182	22.2957
	1.4927	1.4936	1.4892
0	28.8561	28.5285	28.5425
	8.6489	8.7576	8.7477

Eigenvalue estimate λ_1

∞	1.7107	0.5741	1.7131
	0	0	0
30	1.7162	0.7504	1.7199
	0.0497	0.3777	0.0498
15	1.8634	1.0327	1.8677
	0.2856	0.5357	0.2884
0	10.5379	1.6797	7.3859
	2.7981	1.2625	2.6301

Eigenvalue estimate λ_2

T A B L E I

SNR	SVD,P-L		SVD,PM	
∞	mean =	0	0.4770	-4
	st.dev =	0	0	
30		0.6980 -5	0.5819	-4
		0.1938 -4	0.7575	-4
15		0.2775 -4	0.1991	-3
		0.5746 -4	0.1606	-3
0		0.5305 -2	0.5932	-2
		0.1019 -1	0.1035	-1

First Eigenvector Distances

∞	0.3917 -4	0.6169 -4
	0	0
30	0.1744 -3	0.3283 -3
	0.1162 -3	0.2850 -3
15	0.4618 -2	0.2055 -2
	0.3682 -2	0.1110 -2
0	0.8243 -1	0.7146 -1
	0.2614 -1	0.2938 -1

Second Eigenvector Distances

TABLE II

SNR	SVD		FFT		P-L		PM	
∞	0.30472	+5	0.14050	+4	0.15835	+4	0.27610	+4
30	0.24391	+5	0.14119	+4	0.15859	+4	0.27793	+4
15	0.24538	+5	0.14065	+4	0.15877	+4	0.27506	+4
0	0.25819	+5	0.14029	+4	0.15874	+4	0.27568	+4

Computational Cost
 (measured in time units t_s , where $1 t_s = 26.04166 \text{ } \mu\text{sec}$)

T A B L E I I I

SNR	SVD	P-L	PM
∞	mean= 0.5000	0.5000	0.5000
	st.dev= 0	0	0
30	0.4999	0.4999	0.4999
	0.0013	0.0013	0.0013
15	0.4961	0.4952	0.4962
	0.0157	0.0137	0.0154
0	0.4331	0.4620	0.4551
	0.1334	0.0898	0.1082

Frequency Estimate f_1

∞	0.5200	0.5200	0.5200
	0	0	0
30	0.5201	0.5201	0.5201
	0.0013	0.0013	0.0013
15	0.5251	0.5249	0.5251
	0.0190	0.0141	0.0190
0	0.5717	0.5613	0.5642
	0.1184	0.0893	0.0980

Frequency Estimate f_2

T A B L E IV

References

1. W.S. Liggett, "Passive Sonar: Fitting Models to Multiple Time Series," Signal Processing, Ed. J.W.R. Griffiths et al, Academic Press 1973.
2. N.L. Owsley, "A Recent Trend in Adaptive Spatial Processing for Sensor Arrays: Constrained Adaptation," Signal Processing, Ed. J.W.R. Griffiths, et al, Academic Press 1973.
3. D.W. Tufts, R. Kumaresan, I. Kirsteins, "Data Adaptive Signal Estimation by Singular Value Decomposition of a Data Matrix," Proc. of IEEE, Vol. 70, No. 6, June 1982.
4. A. Cantoni and L. Godara, "Resolving the Directions of Sources in a Correlated Signal Field Incident on an Array," Journ. of Acoust. Soc. Amer., 67(4), April 1980, pp. 1247-1255.
5. G. Bienvenu and L. Kopp, "Adaptive High Resolution Spatial Discrimination of Passive Sources," Underwater Acoustics and Signal Processing, Ed. L. Bjorno, D. Reidel, 1981.
6. N.L. Owsley, "Modal Decomposition of Data Adaptive Spectral Estimates," Proc. Yale Univ. Workshop on Applications of Adaptive Systems Theory, New Haven, CT, May 1981.
7. D.W. Tufts, R. Kumaresan, "Estimation of Frequencies of Multiple Sinusoids: Making Linear Prediction Perform Like Maximum Likelihood," Proc. of the IEEE, Vol. 70, No. 9, September 1982, pp. 975-989.
8. K. Pearson, "On Lines and Planes of Closest Fit to Systems of Points in Space, Phil. Mag., 2 (sixth series), 1901, pp. 559-572.
9. R. Frisch, "Correlation and Scatter in Statistical Variables," Nordic Stat. J., 8, pp. 36-102, 1929.
10. C. Radhakrishna Rao, "The Use and Interpretation of Principal Component Analysis in Applied Research," Technical Report No. 9, Sankhya, 1965.
11. W.K. Pratt, Digital Image Processing, A. Wiley-Interscience Publication, New York, 1978.
12. R. deProny, "Essai Experimentale et Analytique," J. Ecole Polytechnique (Paris), pp. 24-76, 1795.
13. F.B. Hildebrand, Introduction to Numerical Analysis, pp. 378-382, McGraw-Hill Book Company, New York, 1956.
14. C. Lanczos, Applied Analysis, Prentice-Hall, Inc., 1956.
15. D.W. Tufts and R. Kumaresan, "Improved Spectral Resolution II," Proc. ICASSP 80, pp. 592-597, April 1980.
16. Ramdas Kumaresan and D.W. Tufts, "Accurate Parameter Estimation of Noisy Speech-Like Signals," Proceedings of the 1982 IEEE International

Conference on Acoustics, Speech, and Signal Processing (ICASSP 82), pp. 1357-1361.

17. Ramdas Kumaresan and D.W. Tufts, "Estimating the Parameters of Exponentially Damped Sinusoids and Pole-Zero Modeling in Noise," IEEE Trans. Acoust. Speech, Signal Processing, Vol. ASSP-30, No. 6, December 1982, pp. 833-840.
18. T.L. Henderson, "Geometric Methods for Determining System Poles from Transient Response," IEEE Transactions on Acoustics, Speech, and Signal Processing, Vol. ASSP-29, pp. 982-988, October, 1981.
19. S.S. Reddi, "Multiple Source Location - A Digital Approach," IEEE Trans. on Aero. and Elec. Syst., Vol. AES-15, No. 1, pp. 95-105.
20. G. Bienvenu and L. Kopp, "Adaptivity to background Noise Spatial Coherence for High Resolution Passive Methods," Proc. of ICASSP 1980, April 1980, pp. 307-310.
21. R. Schmidt, "Multiple Emitter Location and Signal Parameter Estimation," Proc. RADC Spectral Estimation Workshop, pp. 243-258, Rome, NY, 1979.
22. A.H. Nuttall, "Spectral Analysis of a Univariate Process with Bad Data Points via Maximum Entropy and Linear Predictive Techniques," in NUSC Scientific and Engineering Studies, Spectral Estimation, NUSC, New London, CT, March, 1976.
23. T.J. Ulrych and R.W. Clayton, "Time Series Modelling and Maximum Entropy," Physics of the Earth and Planetary Interiors, Vol. 12, pp. 188-200, August, 1976.
24. S.W. Lang and J.H. McClellan, "Frequency Estimation with Maximum Entropy Spectral Estimators," IEEE Trans. on ASSP, Vol. 28, No. 6, Dec. 1980, pp. 716-724.
25. R.R. Hocking and L.L. Leslie, "Selection of the Best Subset in Regression Analysis," Technometrics, Vol. 9, pp. 537-540, 1967.
26. K. Nakayama, "Permuted Difference Coefficient Digital Filters," 1981 IEEE, ICASSP, Atlanta, GA.
27. K. Nakayama, "Permuted Difference Coefficient Realization of FIR Digital Filters," IEEE Trans. ASSP, Vol. ASSP-30, No. 2, April 1982.
28. G.F. Boudreaux, T.W. Parks, "Discrete Fourier Transform using Summation by Parts," submitted to IEEE Trans. ASSP.
29. R. Kumaresan, D.W. Tufts, L.L. Scharf, "A Prony Method for Noisy Data: Choosing the Signal Components and Selecting the Order in Exponential Signal Models," Report No. 3, December 1982, Dept. of Electrical Engineering, University of Rhode Island, prepared for the Office of Naval Research.

30. Claassen, T.A.C.M. and Mecklenbrauker, W.F.G., "The Wigner Distribution - A Tool for Time-Frequency Signal Analysis - Part II: Discrete Time Signals," Philips J. Research, v. 35, no. 4/5, pp. 276-300, 1980.
31. G.F. Boudreaux-Bartels, "Time-Frequency Signal Processing Algorithms: Analysis and Synthesis using Wigner Distributions," Ph.D. Dissertation, Rice University, Houston, TX, December, 1983.
32. R. Kumaresan and D.W. Tufts, "Improved Spectral Resolution III," Proc. of IEEE, vol. 68, No. 10, October 1980, pp. 1354-1355.
33. D.W. Tufts, I. Kirsteins, R. Kumaresan, "Data Adaptive Detection of a Weak Signal," Trans. on Aerospace and Electronic Systems, Vol. AES-19, No. 2, March 1983.
34. C. Eckart, G. Young, "The Approximation of one Matrix by Another of Lower Rank," Psychometrika, Vol. 1, pp. 211-218, 1936.
35. D.W. Tufts, F. Gianella, I. Kirsteins, L.L. Scharf, "Cramer Rao Bounds on the Accuracy of Autoregressive Parameter Estimators," to be submitted to Trans. ASSP.
36. S. Kay, S. Marple, "Spectrum Analysis - A Modern Perspective," Proc. IEEE, Vol. 69, No. 11, November 1981.
37. G. Golub, C. Van Loan, Matrix Computations, John Hopkins Univ. Press, 1984.
38. D.W. Tufts, C.D. Melissinos, "Simple, Effective Computation of Principal Eigenvectors and their Eigenvalues and Application to High-Resolution Estimation of Frequencies", Proc. ICASSP, Tampa, Florida, 1985.
39. B.N. Parlett, The Symmetric Eigenvalue Problem, Prentice-Hall, 1980.
40. J.J. Dongarra, C.B. Moler, J.R. Bunch, G.W. Stewart, LINPACK User's Guide, Siam, Philadelphia, 1979.
41. C. Davis, W.M. Kahan, "The Rotation of Eigenvectors by a Perturbation. III", Siam J. Numer. Anal., Vol. 7, No. 1, March 1970.
42. R.N. Bracewell, "The Fast Hartley Transform," Proc. IEEE, vol. 72, No. 8, August 1984.
43. R. Kumaresan, P.K. Gupta, "A Real-Arithmetic Prime Factor Fourier Transform Algorithm and Its Implementation," submitted to Trans. ASSP.

OFFICE OF NAVAL RESEARCH
STATISTICS AND PROBABILITY PROGRAM

BASIC DISTRIBUTION LIST
FOR
UNCLASSIFIED TECHNICAL REPORTS

FEBRUARY 1982

Copies	Copies
Statistics and Probability Program (Code 411(SP)) Office of Naval Research Arlington, VA 22217 3	Navy Library National Space Technology Laboratory Attn: Navy Librarian Bay St. Louis, MS 39522 1
Defense Technical Information Center Cameron Station Alexandria, VA 22314 12	U. S. Army Research Office P.O. Box 12211 Attn: Dr. J. Chandra Research Triangle Park, NC 27706 1
Commanding Officer Office of Naval Research Eastern/Central Regional Office Attn: Director for Science Barnes Building 495 Summer Street Boston, MA 02210 1	Director National Security Agency Attn: R51, Dr. Maar Fort Meade, MD 20755 1
Commanding Officer Office of Naval Research Western Regional Office Attn: Dr. Richard Lau 1030 East Green Street Pasadena, CA 91101 1	ATAA-SL, Library U.S. Army TRADOC Systems Analysis Activity Department of the Army White Sands Missile Range, NM 88002 1
U. S. ONR Liaison Office - Far East Attn: Scientific Director APO San Francisco 96503 1	ARI Field Unit-USAREUR Attn: Library c/o ODCSPER HQ USAEREUR & 7th Army APO New York 09403 1
Applied Mathematics Laboratory David Taylor Naval Ship Research and Development Center Attn: Mr. G. H. Gleissner Bethesda, Maryland 20084 1	Library, Code 1424 Naval Postgraduate School Monterey, CA 93940 1
Commandant of the Marine Corps (Code AX) Attn: Dr. A. L. Slafkosky Scientific Advisor Washington, DC 20380 1	Technical Information Division Naval Research Laboratory Washington, DC 20375 1
	OASD (I&L), Pentagon Attn: Mr. Charles S. Smith Washington, DC 20301 1

Copies

Director
AMSAA
Attn: DRXSYP-MP, H. Cohen
Aberdeen Proving Ground, MD 1
21005

Dr. Gerhard Heiche
Naval Air Systems Command
(NAIR 03)
Jefferson Plaza No. 1
Arlington, VA 20360 1

Dr. Barbara Bailar
Associate Director, Statistical
Standards
Bureau of Census
Washington, DC 20233 1

Leon Slavin
Naval Sea Systems Command
(NSEA 05H)
Crystal Mall #4, Rm. 129
Washington, DC 20036 1

B. E. Clark
RR #2, Box 647-B
Graham, NC 27253 1

Naval Underwater Systems Center
Attn: Dr. Derrill J. Bordelon
Code 601
Newport, Rhode Island 02840 1

Naval Coastal Systems Center
Code 741
Attn: Mr. C. M. Bennett
Panama City, FL 32401 1

Naval Electronic Systems Command
(NELEX 612)
Attn: John Schuster
National Center No. 1
Arlington, VA 20360 1

Defense Logistics Studies
Information Exchange
Army Logistics Management Center
Attn: Mr. J. Dowling
Fort Lee, VA 23801 1

Copies

Reliability Analysis Center (RAC)
RADCRBRAC
Attn: I. L. Krulac
Data Coordinator/
Government Programs
Griffiss AFB, New York 13441 1

Technical Library
Naval Ordnance Station
Indian Head, MD 20640 1

Library
Naval Ocean Systems Center
San Diego, CA 92152 1

Technical Library
Bureau of Naval Personnel
Department of the Navy
Washington, DC 20370 1

Mr. Dan Leonard
Code 8105
Naval Ocean Systems Center
San Diego, CA 92152 1

Dr. Alan F. Petty
Code 7930
Naval Research Laboratory
Washington, DC 20375 1

Dr. M. J. Fischer
Defense Communications Agency
Defense Communications Engineering
Center
1860 Wiehle Avenue
Reston, VA 22090 1

Mr. Jim Gates
Code 9211
Fleet Material Support Office
U. S. Navy Supply Center
Mechanicsburg, PA 17055 1

Mr. Ted Tupper
Code M-311C
Military Sealift Command
Department of the Navy
Washington, DC 20390 1

Copies

Copies

Mr. F. R. Del Priori
Code 224
Operational Test and Evaluation
Force (OPTEVFOR)
Norfolk, VA 23511

1

END

FILMED

24-86

DTIC